LECTURE NOTES ON POWER STATION ENGINEERING



Complied By

Mr. BHAGABAN HANSDAH

(Lecturer in Department of Mechanical Engineering)

MECHANICAL ENGINEERING
6th SEMESTER
S.S.I.T POLYTECHNIC, KALAKAD

Introduction

A power plantquan be considered as a machinary set up that produces and solelivers in flow stop mechanical on electrical werengy i Generatori. and considered as the main equipment for the electric power generation. It g generates electricity when it is driven by a prime mover on the basic of the types of prime movercoursed, power plants · ane classified. and remos sound winds evenden tidel enender une lear The major power plants one There i courter give eneagy controvely * Steam power plants turning * Diesel power plant * Gos turbine power plant * Nuclear power plant no pel posse si dido mitato Sourcers of Lougy no Isiatustas Consumon for ite own several Energy Cources are classified aspower Textion. Captive power plants 7 Conventional Energy Sources on Non-Renewable. Energy + Sources. 7 Non-Conventional Energy Cources on Renewable theragy sources. Conventional Energy Sources -There Sounces one finite and

exhaustible of Once Consumed these sources

Page Na.:__

Connot be neplaced: Examples of these sources are energy from coal, timber, petroleum, lignite, natural gas, fossible fuels, nuclear fuels etc. Non-Conventional theray Sources These Courses are confineris and non-exhaustible. Examples of these sources are geothermal energy wind energy, tidal energy, nuclear These Cources give energy continously without depletionment and + + Merel Priver Mont Captever power Station - 100 + ctation which is used by an industrial or commercial energy consumer for its own energy - Concumptions is Known an Captive power station. Captive power plants - con rexchange their Surplus energy with the grid stancing Central of tations Station which is not made for the delf user for of the service industries ones with como assid & modes

Date:____

8	
	Central power station. It generates more
	nawer than the capture power plant.
	PHI CONTABLE por large Scale power
	agrenation withere stations are located
S	buttings of the end users and
	connected to a high woltage trans-
	mission metadanes. The electricity
1	generated from these ctations are
1	purchased by the consumers.
	- sor whisher energy starting inc
07	Classification of posser plants
N	Trease fort and property
1	Conventional power Non- Conventional
	plants powers plants.
	The state of the s
3	Steam Thurman power & Solar base power
	plants plant.
-	plants. Diesel power plants > Wind Energy power Dias turbine power plant
1/2	s Gas turbine powers plant
	plantes stones of bloothermy supower
	Hydro- Electrec with plants sound
	power plants. Tight Wave theragy
	o' Nuclear power power plant.
	plants. Deean theremy Energe
	name: stant sound conversions plant.
-	and trong propagat, Bromass Energy
-	stanson of somo conver to generate
-	Thermoexectaic
	and of find and to Openeria-farcas
2	something beceeses paralet due
	and thingbons it is not
	environment friendly.
3	Page No.:

Importance of Electrical Power -The importance of electricity imagination. In every field there is neccessity of electricity. The importance of efectned powers be cenderstood from tits wide anes of sapplication Some of the most notable uses of electricity are-Enterctainment, Heathcane, Engineering Treansport and Communication, outdoor Household, Commercial, Office, ful ong space etc. Drowie of Method of tectrical. The various courses which one wed to generate electric. power are in discussed below of steam power plants Known as Coal-fined power plants use Steam as a source to generate electricity. But the flue emitted by the plant to the atmosphere possesses harmful gases and therefore It is not environment friendly. Page No.

Date

7 But it is now a major electricit generation plant. Letter til endere at the Habitar exemple. Hydro power to + The greavitational force of flowing water is utilized in bydro power plants to kun the turbinel. I'm these plants, water is forced to posses kinatic and pressure energy which ex convented into mechanical energy on the notation of forms turbine. turbine. 7 1+-10 a clean and nenewable resource of from which electricity + As compared to fossel-fuel - powered energy plants, bydroelectric power plants emit fewer ogreenhause gases. 7 The construction of hydroelectric power plants and danc requires huge investment. " Course contract and care waited with Muclear powersewage and upply where ever the 7 Nuclear power plants generales high amount of electricity from nuclear bission reaction using aganium as feel. 7 Nuclear power plants require 100 Quantities of fuel but produce a

Stanted, it ran efficiently none of 12 is more neliable compared to menewable courtes of energy Such as solan and wind. 7 Po these plants, water RT convented into steam after neceiving heaf energy from at the nuclear reaction wands they Steam Es used in the turbine bon energy Conversion. Dresel Englise power-7 This is weed for Small-Scale using diesel as finel. - Diesel is a non-nenewable source of energy which makes there plants non-durable. They are installed in places where there is no easy availability of atternative power Sources and are mainly used as a backup for aninterrupted power cupply whenever there are outages. 7 It is considered as unsuitable for high mainfainage costs and diesel prices. + Aluclan pouls plack the wine law Guartities of freet my produce a


Page No.:.-

Wind - Domer - Domer - Daniel - 1 7 Wind furbines captunes | Kinetic energy promocusing to and convert it into electricity. The amount of energy depends on speed of the wing. 7 14 is a nenewable source of energy 7 Mind power projects typically requir huge capital expenditure. After the wind tensiner one builty operational costs involved in maintaining wind power plante are low and they are generally considered to be relatively cost - appoisson effective. Solar power-1 Porth engin -> Solar energy splante convert energy from the soon into thermal on electrical energy. Don gives the nenewable tenengy Counces and 7 They do not require high maintanance rand cast for cabout 20 to 25 vyears of buit inequiner high initial costs for installation of harden feet squeeze from pronoed soin Tigal power-news your 7 Tidal energy is generaled from conventing energy from the borce tides into power. This power is created when tides notate submerged

THERMAL POWER STATION

A theremal power station on a coal fined thermal power plant uses coal as the primary fuel Hent released from the burning of carl is used to the water to make superheated Steam for driving the steam teenbine. It the most conventional method of generating electric power with hogy high efficiency. A steam power plant convents the chemical energy of the fossil fuels (Cook oil, gas) into mechanical / Electrical energy. This is achived by raising the Steam in the shockers, expanding through the turbines and coupling the Convents in mechanical energy to electrical energy. The following two perpose can be served by a steam power plant: 1. To produce electric power. 2. To proque cteam for inquestrial purpose besides producing electric power. The steam may be used for varying purpose in the industries such as textiles, food manufacture, paper mille, sugar mills, and néfinenses etc.


Page No.:



The different types of systems
and components used in steam power
plant one par follows -
as before margity of roulded by the
2 Boilegain freig puilbour la
Turbine scanol Clana a shidred to
2) Condenserie 11 bell sei lais
+ Cooling tower
> Coal handling System
7 Ach handling System
) Drought Cyctem
-) teed water treatment plant
7 pumping system
> Mounting Cike Safety valve, Stop
valve, priessure gauge and water
-) Accessories like Air preheater,
economizer, Super heater and
The factor of the state of the
Electricity Storage and distribution
cuctern storage and distribution
T T
Layout of thermal plant can be excelled
under ctord be division be
Companies 200 1013 T. Dian
Cercuits.
Coal and ash correct-
The same of the sa
> Coal and ash circuit in theremal plant
layout mainly takes core of supplying
the bocker with coal from the
Page No.:

stomage for combustion and collect from the boiler coal and Supply to Storage, preparation plant coal handling 2 and dispose 27 Doller Ash Handling Unit Air and gas concuet STOLD AIR FROM ATMOSPHERE TO ATMOSP PRE HEATER FLUE GAS FIVE ECONOMISER FLUE SUPER HEATER

7 Aire and goe circuit in a thurnal power plant cayout mainly takes come of supplying preheated girmobtained from the air preheater to the burnace and meleasing the exhaust gas from the furnance after the combustion of > Atmospheric air is drawn into the Air preheater through the forced draught for where air he heated by the shot free gas coming out from > Flue gas having very high temperate is wood in the Superheater, economizer and our preheater where its heat is necovered appear that the flue gas is shouses to through the electrostation precépitator for nemoving dust from the gas and then gas es drawn ento the chimney by the induced drought for to release the gae to atmosphere. Feed Mater and Steam Cincuit -) The water and Steam circuit in a thermal power plant layout mainly taker care of feeding not water obtained from the economizer to the boiler and Supplying Steam obtained from the boiler to the turbine to generale power.



Page No.

Date:____

15	
	> Cooling water is possed through the
10	condenser where the steam is condensed.
Ī	The worker after being heated by Steam
311	is discharged to cooling tower. Cooling
	water Circuit can also be a closed
	system where the cooled water is
	cont toward consine toward for mores
-	sent through cooling towers for ne-use
	in the power plant. The cooling water
8	circulation in the condenser of a
Ť	thermal power plant layout helps in
	maintaining a low pressure in the
_	Congenser.
	The contract of the second for
76.	Curant various separate to canal be
_	
	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1
7	St. 1 St. Annual St. Ast. Ast. 18
	The state of the s
10	2-100 C 2-100
H	The state of the s
0	
1	acarpain (Text diagram)
+	NEWS OF THE STATE
10	- Paracipla Labour Gald a Capital of
· Co	- ed to poden or of the constant to the
13	The state of the s
	The board of the second of the
-	

Page No.

1. Isothermed expansion In the process 1-2 shows the isothermal expansion process. In this poiler process water gets beated in the boiler at constant temperature (T, = T2) and pressure (P = P2) and gets convented into steam. Entappy increases from S, to S2 and dry steam is collected at state 2.

Heat absorbed by water (P, 2) and solver.

2. Reversible adiabatic expansion—
In the process 2-3 shows the reversible adiabatic expansion process.
In this process steam expands inside the turbine at constant entropy (ci=52) and produce shaft power. Steam becomes wet at state 3. Pressure and temperature get changed from state 2-3.

3. Isothermal compression -

In the process 3-9 shows the isothermal compression process. In this process steam gets congensed in the condenser at constant pressure (P3 = Pq) and constant temperature (T3=T4). Entropy decreases from S3 to S4 and wet steam is collected at state 3. Heat rejected from Steam

(83-4) = T3 (S3-S4) = T3 (S2-S1)

Page No.

Paga No.: -

later.....

* It es difficult to control the quality of the condensate coming out of the * The efficiency of the carnot cycle is greatly affected by the temperature Ti * The cycle iconstill more difficult to operate in practice with superheated Steam . Just a mai late trained to Chann of Clata 2 m a stan Ranking Cycle - har bear and the test was done the management A Steam power plant using steam as working Substance works barically on Ranking Cycle. The T-S diagram for Rankine cycle ic shown below. Medical State of State of the Q1-2 Turbine > WITH are parties protection was an Boiler man 19 had by Condenser Cooling water Wp - Quit out out Pump per quantity of 193-4 (Rankine cycle) estable of Line or trade war a secure for the second (T-s diagram) 3 -> 52 No. 3

Processor of described below 1. Isothermal Expansion shows the bets proces contunated water at state 1 is converted into day saturated Steam at State 2 in a Steam boiler at constant pressure (Pr=P2). Mater absorbed the latent heat

Of vapounization (hfg = Afg2) and

Converted into dry Saturated Steam

Heat absorb 1-2 = hfg2 = h2-hf2 2. Reversible adiabatic or kentropic expansion process in process 2-3 shows the nevencible adjubatic on isentropic expansion process in this process dry Caturated Steam at State 2 expande isentappically in turbine to State 3. Steam at state 3 is wet. Workdone 2-3 = Turbine work = 42-43 3. Icothermal Compression process

In process 3-4 process chows

the Isothermal Compression process.

In this process exhaust steam of

turbine is cooled by cold water

in the Condenser at constant

pressure (B=P4) and Constant

temperature (T3=T4). Steam release latent heat of vapourization and

convented into saturated water.
The state of the s
Amount of heat rejected in proces
203-4= hfg3 = b3 = b fq
to you the since of the state o
1. Reversible adjubatic on Isentropic
process - proces
In process 4-1 shows the
reversible adiabatic on sentropic process
In this process saturated water in
drawn by the pump and feed into
the boiler.
The state of the s
Work done in this process 4-1=
Dump of work qubit bf412)
Character to the second of the
Efficiency of Rankine cycle-
Efficiency = Net Workdone Heat supplied
Heat supplied
The second of th
= NT - WP
91-2
= (h2-h3)-(h1-h4)
(salation to tetromorphis (his bear))
the first the transfer of the transfer of the second of th
If pump work is neglected then Wp = 0
The second of the second of the second of the second
affectionery reaction is surveine office
income acheen supplies apprecion to it
1 cycles speciercy.
The same of the sa

Efficiency natio = Thenmal Efficiency Rookine Ebficiency

Thermal Efficiency = 3600 x P

Thermal efficiency = 3600 x P

m(h2=hf8)

The state of the second Where, when the mine

P.= power devloped in KW m= mass of steam supplied.

Monx reation

to the turbine work.

Monk matio = Turbine wonk - Compressor Turbine wonk

Specific steam consumption -

It is defind as the mass of steam supplied to the turbine to deviop unit power output. To is also known as steam materion specific mate of flow of steen.

Specific steam consumption = 3600 Kg/KWh

Page No.: ...

6. R104 = SF2 TIM, SFg211 = 0.521 + nc, h Fg 2 50.512 + M2 X 7.809 : 104 - 0.521 7.809 +P.586 - 0.728 - 126) 2 P.S. F. R. 1 S. 2132 - 15 7. 29 1 h2= bf2+ ol2 bfg2 = 151.5 + 0.728 × 2415.9 = 1910.27 KJ/Kg

Turbêne work,

THE BUTTO WILLOWALL ON THE REAL BY THE Wyundine = h,-h, = 2802-1910.27

= 891.73 KJ/Kg

Pumptwonk, training

Wpump = hfq - hfg = Vf(P1-P2)

0.001 (28-0.06) X 105

maring to a still a still a maring to the still a maring --- 1 1 1 1 1 2 = 2.79 KJ/Kg + Sign

I be housedook durp and California

bfq = hf3+2.79=1515+2.79 MANAGER PERSON DE SINSA RANKTYKE

.. Net work, when your

Wret = Weurbine - Wpump

Page No ..

Date

question 100.3 - A steam tunbice	AVEN TO
neceives steam at 15 bars and 8	50°C
and exhausts to the condenser a	t con
0.6 bar. For the ideal Ranking	cucle
operating between these two um	+5.
determine the (i) heat coupplied,	
is been period (iii) and whom don	0
is) herf rejected, (iii) net work don	
iv) thermal efficiency	The same
Section 100 Section 100 has	0 = al
Question no. 4 - Stieum at 50 bar	NO. IN CONTRACTOR OF THE PARTY
400°C expande inia Rankine cycle	
0.5 bar. For a mass flow reate	-06
150 Kg/c of moteam determine	4 (00)
1) power devloped, (ii) thermal e	Spicier
iii) Specific S-learn Consumption.	1557 (1004)
The state of the s	
Question no. 5 - Dry and Satur	the same of the sa
Steam of 150 box is supplied	to a
Heam turbine working on Ranki	
cycle. The vexbauef faces place	at
1 bar. Calculate (i) Rankine ef	ficien
ii) Steam Consumption per KNh Is	the
efficiency matio in 0.65.	
OF THE PROPERTY OF THE PROPERTY OF THE PARTY	17
Mary Ociobe canalcana i - 25	
down Frait laduli) xideparis	
TELL DE DESCRIPTION OF THE STATE OF THE	34.98
The filler made in Handres pari	
8- Lando a Kija and Lang	
St so with Extra D Chip to football that I see the	Example 1
Sangal (in Champing - 12)	
SEG Ser La Cillant Bandlet La Cillant	

	List.	of there	pal power splante	1 Stations	
200	in India-				
4	sc. No State power of the capacity				
Eugla	SCONO	· States	Down of Hor	Capocity	
21	Total Control	1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 -	- 120 1-2 1 201	(May	
	Tel	Andre	Kottagndam	240	
4/3	water w	an DHANACE	1111 12 12 12 12 111	1000	
	2.	Assam	Gauhate	40	
The back	- 3.	Bihar	(i) Banauni	110	
bas	Mich	me de m	(ii) BOKAROS	225	
10	19.00	exist atte	(iii) Patratury	Soo	
7.0	s 4. m	Delhine	il Rajaghat anglo	350	
1	4 - 2	ale tena in	Inpathermal P. 5)	14 050	
Shiring	c tai	(ii) 4: 111	(ii) Badarpur	1 300	
1	5.	Gujarat	(i) Dhuvarani	530	
Acres	to Freion C		(ii) Ukai	240	
beta	1146:3	Hanyanan	(i) Famida bad	200	
£0 a	post	79 2 50	(ii) paripat to	211230	
50	7.0	Madhyan	The Kabitanil	MARO	
af	Mare	Pragesh	(1) satpura	01300	
ringiania	40 min		(iii) Amarkantak.	180	
426	8.	Maharastra	(1) Nagporo (Konigh)	to 480	
	- Const of	0.29	(II) Nask pros	1:280	
1888	The state of	14P	(iii) Paras	90	
	-9.	odieha	Talchen	254	
- m-2	10.	Tamil Naga	(i) Neyveli	600	
1	-70.5	The said of the control of the contr	(ii) Eunorce	450	
MIL. NE	110	Uttan prad.	(i) Harduagary	550	
	STORY W	1911年 1911年 11911年 11911日 1191日	(ii) Obra	480	
	-12.	West	(i) Santalgih	420	
	Marie Sal	Bengal	(ii) Chandra pur	420	
45	- Chicago -	2	(iii) Bandel	330	

Date:____

C. NO	. Name of the plant.	Capacity (Mr
4.	Jinday Steel and power Ita	810
2.	NALCO (+q. Captive power plant	1200
3.	GIMR - Friengy	1050
43.	Vedanta Ctd. , IPP and CPR	Man Andrews
s.	Talchen Cupier thermal	3000
	Jindal India Thermal	1200
7.	Roulkela Steel plant (CPP-1)	bot 100
8.	Thermal power Station (OPGC)	120
9.	HINDALCO Industries (+q.	467
10.	TATA Bhusan power &	370
And	ntd. the cold air into	(separa

Boiler accessories are the Set of devices that are used to increase the efficiency of the boiler. These devices improve the boiler operation.

Page No.:

The following are some of the accessories which are used in boiler. Ain Pre heater -0304 Hented -Tubes Babbles - Air in Tubulan type air preheater. + It is a heaf exchanger which Converts. the cold air into hot air from the heat exchange between atmospherec air and flue gas. > It recovered heaf from the flue gas coming out of the Economizer) It is installed between the

economicer and the chimney weter and attacked about and The air is required for the purpose of Combustion is glawn through the ain preheater where its temperatu is reacced. It is then passed through ducts to the furnance I he preheaded ain gives higher furnance temperature which negults in more hear transfer to the water and thus increases the evaporative Capacity per Kg of fact. It increases * Economizer -Converte the Cold water into hot water from the heaf exchange between feed water and flue gas.

The necovers wheat from the flue gas coming out of the Superheater. -) It improves the economy of the Steam 60ilegson ale 1124 Carrierat a calerfamentichichiche from * Super herder - was trusted the Steam Coming from the boiler into

Page No.:

Supenhended Steam from the heaf exchange between Steam and flue It recovered the heaf from five gas Coming out of boilers of Its purpose to increase the temperes Saturated Steam without raising its pressure to It is generally as integral part of a boiler which flue gases from the furnantion Electrostatic Precipitator Electric Charged Discharge place

bild particles regetive polari

gal polari

Uncharged Discharge place

Uncharged Discharge place

Particles of 14 uses electrostatic fonce to Separate dust particles from exhaust gases: ? The contaminated exhaust gas from through the possage from by a

e			
Dot	C:	-	-

number of high voltage, dinect-current discharge electrodes and grounded collecting electrodes.

The airborns particles peceives negetive charge while passing through the scharge and collecting relections.

These changed panficles get attract towards the positively changed grounded on collecting electrode and adhere to it.

The collected material on the collecting electrodes is remove by rapping on vibrating the collecting electrodes.

Need of Boiler Mountings-

Boiler mountings are the set of safely devices installed on the boiler for its safe operation. There are very essential for a boiler to operate it Safely.

The following are come of the mounting which are used in boiler.

* Pressure gauge - It is used to measure the pressure of steam inside the Boiler.

Page No.: ___

to indicate the water level in the boiler. * Safety Valve - It is used to blows off the reverse steam when steam pressure reaches above Safety level. ייים בין יי בילים * Steam Stop Naive It is used to stop the steam in the boiler mequined. pan in the manual training * Blow off valve - It is used to stop to stomo blow of the impurities on segiments settled idown in the iboilerin ve valionisto igailor" 27 receipting on this lead the continue * Feed cheark valve - It en used to control the flow of water from feed pump to the boilers Openation of Boiler 9 The boder es a closed vessel The Convert water into Steam. Water is supplied into the boiler drum that are formed by burning fuel in the furnance. When the steam at the boiler; the steam stop valve

releases the Steam. This steam is superheated in a superheater before it is supplied into the turbine. while the same of the same of

-) The various mountings and accessories of boiler helps to nun the boiler Draught Systems

différence between absolute gas pressure within a furnance on Chimney and atmosphenica pressure which causes


- > Draught + Can + be obtained by the on a combination of these
 - 7 Boiler draught provide an edequate can throw out the sexhaust gases of Combuction from the Combuction chambe It can discharge flue gases to the asmosphere francish the Chimney.
 - I Then draughts may be classified as Natural Draught and Antificial Dreaught. was appeared in all and

Date:_____

gas at a high level. A Decaphantager laft Natural Draught -) Maximum pressure avoilable for producing a dreaught by the channey ?c course boiled in the contraction occurrent) The available straught openeased Enchease in toutside ains temperature. > + the gas have s-to be discharged at high temperature which towered the plant overall efficiency. Destronged Buy the weeks where Artificial Draught -I When the draught Exprieduced by any other means except channey it is known al Antificial Draught. or my market a had a hard to the or and To meet the high draught demand, Antificial draught scystem is used which is classified as steam j'et draught and mechanical draught Mechanical mongraphy CHESTON OF THE SOURCE OF SHOULD FIRE FOR FIRE F + It is an artificial draught where fore on blowered by the help of es francial to blow towness the 7 11 is more conomical and lets control

Page No.:

Date:__-_



) Balanced annually withe combination of forced draught and induced mangati. I I overcomes the difficulties that are seen by using the formed draws on induced draught alone. It mainfain the balance. 3) The forred draught fan supplies the Combustion our for better. combustion of fael sand overcomes the nepretance of first bed The tradited strought - nemovee the fine gas and excess ain from the forenance and helpento bootson referere it through channey. It helps to mantain the pressures of morde the furnance below atmospheric 7 It - the inforced draught is applied alone, there will be high pressure in the furnance of the courses difficultie in lightening and inspecting the boiler. There is posibility of blowing out of fine from the furnance which may disable the furnance work. The induced draught is used alone, there will be difficulties in inspecting The boiling because cold air may not into the furniance as the pressure inside The forenance is under atmospheric pressure.

Page No.:

Date:_____

Advantaged of Antibicial or Mechanical
Draught
a Low Is riffered wards on
I The incheases the most enof combustion
bon wahiche lowingrade in freel can be
used in funnance 60, feel cost es
reduced for the figure of the state
+ The indesired invalue of indianight can
be produced, which is not obtained
in natural draughtonis
7 D+ requeen the smoke level and reduce
the height sof Chimney as assist
) It is more iconamical sond its control
Psoceasy. site with soil nest test of
2 (14) cavaning energy. It strimproved the
plant afficiency as maximum heat can
be cetilized.
> 14 necluces fuel concumption and make
boiler roperations & Cheaperages round
The sales I have been been and the sales and the sales and the sales and the sales are the sales and the sales are the sales and the sales are
Desadvantages of Antificación Mechanica
Draught + 3 c at 11011 no at 12.
> The invital costenius hugh. II
> The mannings coef is also high que
to consumption of electricity but it is
compensated by other savings.
-) Fors and blowers produce noise.
The second of th
insochusatique of them territor-
opposit at systematers with the charge

Page No.I

Date:____

The state of the s
in power demand companed to reciprocation
engines and guest feetorist.
> D+ taxes long Start up time compared
to reciprocating engines and gas tunbines
on the takes long stand up time companed to reciprocating engines and gas tunbines only is less efficient at pant toad
conditions than necliprocating engines an
gas furbines is standard of
gas furbines is standard and
Classification of Cteam tanbine
the contract of the same of th
The steam turbines may ube
Classified into the following types -
* Accordings to the mode of steam action
the die su passens and low- masseurs
Impulse furbine . 10011 1001.7
- Reaction function
the treatment touch curiousting.
* According to the direction of steam flow-
-2016 111 - Free 21 CC
7 Axial flow turbine
-) Radial blow turbine all cold
+ Acceptain the training of the
* According to the exhaust condition of steam
7 Condensing turbine
The time that the same of the
* According to the pressure of steam -
The state of the s
7 High pressure tunbine
- Medium pressure tunbine
> Low pressure furbine

frist song According to the number of stages--) Single Stage tunbine. Flements of Cteam tunbine The components of cteam turbine -> The casing Contains the rector and nozzles through which the steam vis expanded wit and being it is on The steam bother is a connected with the higher pressure and low-pressure of team cheef and casing protect the turbine from currounding. + Dr encloses the steam inside the tenblne. SETULATION TRIANCE * Nozzles - ioni- wall lails 7 These are used to increase the Kinefic energy of steam ma2/2 * Roton - Salvania Tasandonia > The noton consists of disc mounted on a shaff. Number of blades are mounted on the peripher of the disc. -) The shaff extends beyond the casing . One end of the shatt is Connected with the governer and

Page No.:


1	other send is coupled with the shalf
5	of the ighternators will a les tons
3	The main function of the motor is
	to convert the thermal renergy of the
1	incoming cheam winto kinetic lenergy.
9	in a weeking the party of the weeking of the state of the
·	* Blades - 12ti met cont and min
	I Number of blades mounted on the
	periphery of the dise are used to
	receive on the cteam consist on Their are
X	used for energy conversation and
1	pressure and velocity variations
	ecces sugar est - teaming man and a
	* Gloverner sai
	-) Those weed to maintain the mean
	equilibrium speed of the steam turbine.
	to netwer soil of the for escourant with set
5	Difference between Impute and neaction
5.0	tunbinant lengar lengared and regulated
0	1 egolenet a manipul de est parapole de anientes
_	Impulse Turbine Reaction Turbine
	1. The steam flows 1. The steam blows
-	1. The Steam flows 1. The Steam flows
-	through the norter firef through guide
-	and impinge on the mechanism and then
0.0	moving blades. through the moving
1	a The and the street of the attention
-	2. The steam impinger 2. The steam glige
	on the buckets with over the moving
1	Kinetic schengy! vaner with pressure
1	stand kinetic energy.
4	· Can be availand and by wishing


3. The ofeam money on 3. The steam must be may not be admitted admitted over the over the whole whole circumference. Cincin benence in 11 4. The steam pressure of The steam pressure nemains constant is neduced during the flow through through the moving moving blodes. 5. The negative velocity 5. The nelative of steam while proverount of steam gliding over the to while gliding over constant. -- the moving blades 6. The blages are bit The blages are Symmetrical. Symmetrical. 7. The number of 7. The number of less bon the same mone for the same power devloped. power developed. Gloverning of Steam Toubine 7. The function of a governor on to Steam tentine. 7 When the steam turbine is connection to drive an alternator, there may be variation of load. According to the load on the alternator, turbics Can be overcome by using a

L			
	governing method, by alliquit and		
	governing method. It will be all		
ı	+ The different governing methods are-		
I	son the charge sine - and dealy malaned.		
ı			
İ	* Throttles governings is many		
	* By - Park governing of the		
J	* Mossles governing alling polar		
1	destaurant and continue close to		
	Throtthe Governing -+ mail . sile		
7	28 - robine of remediation - a militime of the series		
•	a tax area area area area area area area ar		
	The state of the s		
	Fly balls		
Š	1 OVOR		
	+wicran Lever		
	Cleeve A. State Marie Control of the		
	Steam - Court Con		
	moto teat in a site of face of Main "Valve		
	13 Bour the sale religion of another		
3.5	- secolitist in the second control control		
	Devel to a Turbine		
	10 2 300 1 300 1 300 1 300 1		
	- 1 - 10 Comment to the total and the total		
	- course many sonder avous the trans		
Ī	town part from the Charlestone was		
1	7 This method every Gimple and less		
	costly. This is weed witon reques inlet		
	steam pressure by throttle valve		
	operated by governing mechanism on		
	parts loads.		
	> An oil relay is used to operate		
	Page No.:		

Date

the throttle valver I When the turbine works on less than full load condition; the load on the turbine suddenly released, governer speed increases on with noten speed and steve motors upward so, nelay piston under oil pressure moves gownward and partially closes throthe valve. Then the observe comes to its position when equilibrium speed is 一个一个一个 By-Pass Groverning 7- This method is used in modern impulse funbine operating at a very > In this method - the - whole - Steam entene the nozzle box through a throttle valve. This valve controls the Speed of turbine for all load up to economical loads for the loads mone than economical coad, the by-pass valve opens and allows the steam to pass from the first stage nozzle box into steam belt and so into the fourth is stage nousle when the 10ad Stabilizes withe valve operan closes in it to me the series of the series CIOSPI - The control of the wall to color to the color





Mathematically, and in the sales Norma efficiency (M) DHact · Relation between efficiencles -Stage efficiency (7) = Black efficiency (76) x Nozzle efficiency Steam Condensem the server of Description (212) A Steam Condenser issue helosed vessel into which the steam is exhausted, and Condensed after doing work in the turbine. A steam condenser has the following two objectives. 1. The main object of condenser is to maintain a low pressure l'below atmospheric pressure) so as to draw the moximum possible energy from steam. Co, the efficiency of plant can incheared as set only in the properties of 2. 14 is used to supply pure feed water to the hot well, from where it is pumped back to them boiler work washing when to prove a face in the date of Clossification of Condencers clossified into the following types -

* Jet condensers on mixing type condensers 2. Counter flow on low-level - Jet condenser 3. Barometric on high-level Jet 13 Conblenger 1. Ejector Condencer * Sunface Condencents on non-mixing type condensers. Down blow Queface Condencer 2. Central flow Surface Condenser 3. Rogenerative Purface condenser 4. Evaporative Condenser. the state of the state of the Elemente of Steams Condensing A steam condending plant consists of the following elemente · Condensen - A condensen is the heaf exchanger in which heaf exchange occient between the bot exhaust Steam of the turbine and cord law pressu · Air Extraction pumpto main tain the vaccam pressure inside of the condenser.

Date:____

The state of the s	CONTROL OF THE PROPERTY OF THE
A Conde	ocate Extraction pump + It is a
	escure pump which see used to
and the second s	the Condensed them the
	er and to supply it into the
	H. I. Mais bearing the service of th
A Carlina	Thister City III A to Co. Co.
	Water Circulating pump - 1/4 85
	Circulating the cooling tower
	denser. Pelmeloson
	CALL THE THE THE THE THE THE THE THE
	Well - 14 8s. a tank which stones
the co	ndencate which come from the
condenc	ernithen is the
- 8	beilen the tring of the parties
D Cooling	g Tower - Dt is so heat exhanger
in whi	th hot water extracted from
	ndenser transfer herf to the cold
	enic ain and gets T convented into
cold w	ater. This cold water is cupplied
The state of the s	e Condenser by coolings water puny
to nen	sove heart brom steam. Some
amount	of water gets vaponized in the
coolings	However Teinington to the ?
Dr. war	regarded survey and language new kang To
D Boiles	Teed pump = At is an pump
which	Es used to supply the water
The state of the s	not well to the boilers
U	fire the Europeaning on the
	eupop Water pump - When there es
	ney of cooling waters makeup
water	needs to be added by the
help o	t the makeup water pump
TIGHT.	Page No.:
	Lage M0.1

to opeliver frenk water from a sung to the condensing plants Steam THE THERMAN TO THE AND Turbine Turbine Boiler Cooling 17 2 trans (intermedical months Condenser Cooling water Boilen Fred premper Hot well and married instead Cooling Towns -> Cooling tower was cused to negect heat winto the atmosphere. - The cold water exite from the cooling tower is sent into the condension. This worten is convented into hot water after inecciving heat from the steam incide the condenser. Hot water is extracted from the condenser and capplied to the cooling tower where Et 95 cooled by the atmospheric aire not the dist more and the

Page No.:

Date:_____

	Types of Cooling Tawar - 1		
-	the more of colings where the test property		
	Cooling tower can be classified on		
	the bosis of method of air		
	Conception. Such as - mone		
	dedupation blackers disapporte again account		
	* Natural arrangly cooling + tower		
	* Mechanical draught cooling tower		
250	The same of the sa		
	Tronced grought cooling tower		
	7 Tonced draught cooling tower.		
	Spray pond-		
	Laver This - Tiens dead to the		
1	Hot si Spray noise		
7	Water Spray notes		
	Vapour m -> Valer		
	And the second of the second o		
	Cold Water		
	Vapolet the state of the state		
	out Janist Jacobana Co		
	out Water nesenvoin		
	Water nesenvoin		
	tory diza afe rice plant		
	7 A spray pong is a meservoir in		
	which warned water is cooled before		
	neuse by spreaying the worm water		
	with norries into the cooler air.		
) In Spray type cooling method, a		
	Carge Surface of water & exposed		
	for evaporation.		
	ATTER had wanter extracted to the		

conden & supplied to the sunface of the cooling tank and is projected into thin horizontalt sheeter Mozzles are fitted on the sheets There nossles brake up the water into drops. Water groplets gets cooled dee to convection or cold water le The following points should be taken into consideration while Celecting the site for a steam power . + Availability of raw material. -> Nature of lang. > Availability of water windy 7 Transport barrety 2) Ash disposed facilities 2) Availability of Caboun. 2) Size of the plant. 2 load Centre + public problem many do . 7 Future extension. 101 - 2 21 Hall 11 - 11 100 21 101 一ついます ニーカンカーラ アウリントラー アーライン Contraction of the second of the second tella test of the same actioned at their

MUCLEAR POWER STATIONISTA

neacton as here source is known as neclear power of source is known as neclear power of plants Nuclear power of the producing steam from water ... The steam producing steam from water ... The steam produced is used to team the durbine to develop mechanisms power, which can be used by the generator who produce electricity.

Muclear fuel-

Muclear fuel should be fissionable material. Dt can be defind as an element on usotope that underego nuclear fission to produce chain neartion by means of bombardment of neutrons to the necleus of heavy atoms. Examples of uranium atoms in a nuclear fuele one U233, U235 and PU239.

Fentile Maderials-

Some materials are not fissionable by themselves but they can be convented to the fissionable materials by moans of nuclear reaction. These materials are known as fertile materials.

The process of transmutation of fertile materials into fissile materials

Example of fertile material one Pu239

and UB3 rege No.1

ficsile majerials.

U235 21 most constable materia

Page No.

1) is capable to sustain chain reaction. It en concedered as primary fire. U233 and po 239 are artificially produced from The 232 many U238 nespectively are called secondary fuel. topes -150 topes were where and the colours to the the the an any atomin the numbers of electrons = number of protonics This Is independent of neutrons in the nucleus. Atoms having different number of neutron than the number of protons are known as Trotober simpond want soon soul some or are no continue. Trees represent Radioactivity - son sei no monthon atons quality is the court and another Radioactivity, was oniginally discover by Becquerel in 1896. Then phenomenon top spontaneous enission of powerful anadiations exhibited By heavy elements is called madioactivity Radioactivity wis resentially a moucheon phenomenon and issue approved process because the element o changes ite king. Those elements which exhibit this activity and Balled radioactive elements. Example + Oranium, polonium, madium, madon, ionium, thorium, actinium and meshothorium. The radioactive radiations emitted by the radioactive elements are found

THE TENTE TO THE Huclean Fiction - Nuclear fiscion ? I the process Sputs into brogments of a heavy atom sputer nuclei with the nelsage of a heavy. The is carried out by the bombardme atoms. This reaction produce energy as well as neutrone. These masterness neutrons can be need to septet other atoms funther in the chain neartion. Fresion is the sprintered that occurs when a new from College with the necleus of Centain of the heavy at causing the original inucleus to split which canny off most of the severy of fission ar Kineter energy. This process of accompanied by the remised of necessions and alagement mayenes Chain reaction - Nillian 24 popular - bico A Chain reaction of that proce

in which while number of neutrons keeps on multiplying rapidly Cin geometrical progression during fission till whole the fissionable material est disintegrated. The chain reaction will ubecome Self-Sustaining on Self propagating only if a form every neutrons absorbed, at least one fission neutrons becomes available for Cousing fission of another necleus.

Chaint reaction Time (215)

ment point and morning of the chain process

Muclean Facion- of manufactures

Nuclean fixeion as the process

Where the nucles of wighten atoms

Combine to form heavy nucleus with

the nebease of energy. It produces

greater energy than the fixeion neartem

Necessar fueron to be the process of

Page No.:

Combining on fusing two lighten nuclei into a stable and heavier nuccode. In this colonicated plange and of energy is nealeased because man busy.

Deutenium

Deut B Down S Neutron It is thought the energy liber in the sun and other stone of main - sequence type is due to the nuclear fusion near-front occurring at the ven high stellar temperature of 30 million Kon Such process one carried theremo nuclear reactions because they are temperatiene dependent Déférence between Nicclean fission and Willetean fuccom. Pession - Fascon Sucated to commerce to the walls of nucleon is hombandment fuse together w
with neutrons, the the melecies of

Page No.....

	nucleus sputs into	energy.
H	freagments of equal	in almost the Some
	moss and senergy is	when me discussion is all
	nelegrade skalmin	salat rai rate at leave
	2. About one flourength	2. It is possible to have
1	of mass is convented	four thousenoths of
	into energy.	mass convented into
	in son passin plant	The second secon
_	3. Nuclear neaction	3. Recidual problem
	nesiqual problem is	1. A possible adjuantage
	great.	In the House the Address of the Addr
	1. Amount of radio	1. A possible adjuantage
	active material in a	is that the total
3	fission reaction is	amount of radioactive
49	high.	material in a working
		fusion neacton is cikely
	natal fi	to be very much less than that in a fiction neacton.
A	The same and the	than that in a fiction
-	r December of the Con-	neacton.
	5. Because of higher	5. Bleame of cases
	had the borney	radioactive material,
	in Care of post de la	health chosond is much
	6. It is possible to	C Da la antenet
	constant Colland Conference	and frecult to construct
	Lission near-lone wood	Controlled fusion reactor
	have positive immergy	contract of a survey
_	nelease.	and and appropriate
	7. Manageable -lemper -	7. Needs conmanageable
	aftere Is obtained.	dempiratione cike 30
	layer person plant	million olegnes book
	when the war and and and the control of	need has fusion

priocess to occur. * 8 . Reserve 10 f dender 3. Raw fremonable material et not the fusion seem Coolant " - New lean - neacton the Heart Exchangen Cotoan general team Turbine Condenser Electric Generator en to solund In a nuclear power plan the nearton produces

from the nuclear fission of the nuclear quels The heaf milibranted in the meactor is taken up by the coolant Circulating through the reactor come. Hot coolant Plaver the near for and then flow through the tuber of Steam generator + Hot coolant gives up the heart energy to the feed water flowing through the steam generator. The steam co produced expands in the Steam turbine and produce mechanical work. The steam turbine nune an electric generator to produce electricity. The exhaust Iteam can be condensed for recycling pumps one provided to circulate worter. Condensate and freed

Nuclean Reactor A nuclear neactor is an apparatu in which heaf is produced due to nuclear fission chain reaction. The reaction generates contaneous energy from the continuous fusion reaction. During fission Kinutic energy is Convented into thermal energy. The heat produced in the near too is

transferred to the sam coolant which is either used directly on indirectly

by converting into steam. There steam

molowa is wood to redtates the stersine who the therman energy see convented into Contro Coolant

Essential Components of a Muclean peador time part from Chairman Dito the properties to the second 2. Reflector 3. Control of Michaniem - sed sed cool and 1 5. Measuring Nostnuments 6 Shielding it not it landling is the invastor with 1. Reacton Came - monther nearton & cone is the part of a nuclear power plant where fession reaction on chain neaction is made to occur and where fission energy liberted in the form of heat for operating power conversion equipment. The core of the neaston consists of an assemblage of fuel elements, control mode, cooland and moderator have paragraphed in manifestion forestant wherein 2. Reflectorisis and two said of A Reflector is usually placed around the cone to reflect back some of the man neutrons that leak from the lunface of the cone I't is generally made of the came material of moderatory were find up a some we have when the best were 3. Nuclear fire Commonly used nuclear fuell are UR33, URBS, and wpursag. Among these U235 is most nunstable and This is called as primary fuel. U233

and polygone and uzzz nespectively and contemposecondary freep. Control Mechanismut 17: 13+ on tessenteal pans of a neaction and serve the follow r ton Stanting the nearton, to openating tevelor 11. For maintaining at tover, Keep. power production hat a steady Ho in ton skutting the neacton down under normal on mentaency condition 4. Coolant The function of Cooland Estato - premove of the intense heat produced in the reactor and to bring out for being litelised. The desinable characteristics for a neactor coolant and in Low paracates Capture 11: Low melting point no no High booking point iv. Chemical and near floor stability. v. Low Viscosity the start Non-toxice & was the said to some VII. Non - Connociveness . . . Minimum induced activity

x. High specific wheat to the service of cuse court care autons a finance and weeks sounders the Commonly used Coolants + Santiwax R a by The second River in the State of 5. Moderator + Materiala in the which slow down the neutrons neleased from fession so that they Cause more fission. Had Dad Cheavy water He (gas); Be and a (ognaphite) are the Commonly weed moderatorie and we are of love to the dead with fire to the 6. Measuring Asstrumenter Main Instrument required 11. for the prespose of measuring thermal newtron flux which determines the power devlopment the reactor. Superson pooren plante etherdrant spoulers plant 7. Shielding-Shirlding rich recessary in order to - mais a minute of the and it in protect the swallen of the nearton vessel from madiations damage, and alco to so the state of result in a serie 11. profect openating personnel from exposeine to madiation. in a man in the first of the man and some and a second or a second of the second of th Realton Vessel- It enclose the various parts incide the reactor including the core, shield, reflector etc. take at 1120 - Li a santa se to the Side Lot have

populated area there is suitable

Page No.1

	PROMESSING AND THE PROPERTY OF	
	to avoid the micked	of Supplies of fuel,
	of readioactive	water and fransport.
	pollution	sisting of the
	to spangues & 2 of Buren ?	install a manufacture
	1. It has high initial	A. Drachar low initial
9	cost in companisons	coef in companison
	to thermal power in	
2	plants manning rainer	THE CONTRACT OF STREET
	5. It has low operating	
	cost in companison to	cost in companion to
	thermal power plante	
	existed and larger	
	6. Nuclear fuels cike	
1	vicasium one the courter	
ķ	of power Fuels onen	Source is comitted.
	available Sufficiently	DI TOTAL CONTRACTOR OF THE PROPERTY OF THE PRO
	ertall wather began	in in a superior
2	7. Overall efficiency is	7. Ovircall efficiency
M.	more surface makes	
	Louis - continuer sales E	tone low and
	8. It Stante easily is	8. It Haver more time
	the war to want I man	for stanting the
	with the state of	Ciplantavel-new
	9. Standby losses are	9. Standby losser are
1	for shurten powering	Samored Down til
5	tenson postant not	
	10. Better in environmen	from Least environment
	friendly.	& triangly .
	with laws some plane	The fore fore
	and land Down Plane.	100 2 1 - 18 hr 10 - 18 - 2 mile
	and removed as the	

Disposal of nuclean process blasses material. It is usually a byproduce hazardous to environment and lev. organisms, for it he negulated by government agencier in order to prieter human health and the environment. in the property of the trip with the property to Radioactivity naturally decays over time. So isolated and confined madionetive waster posses no book threat a sufficient time peniod. This waspen cannoben well in managed for disposal. This approached to manage radioactive waite by Signegation and Storage bon shortcived waster near-Conface disposal for low and some intermmediate Cevel waste, and ideep bunkal for parfitioning / transmutation for the high-level waste. Sitz Selection fon Nuelean powen plan Considered while selecting the cite for a nuclear power plant. 7 The site should be nearer to a niver, reservoir on sea to palfel

the majorinement of water for the plant. lines and to reduce the coef of power indelevened wito withe consumer, the plant should be located indurer to the load centre. + The power plant should be located fan away from populating area avoid the traditactive horard. > The power plant should have easy accessibility through rail and road transportation facilities. > The waste of nuclear power plant are radioactive and there should be Sufficient space near the plant site. for the disposal of waster. There should be considerably no neck of disaster. geological, hydrological, meterological and Seismological report for the location. List of nuclear power plants-The various nuclear power plants Situated in India are as follows-1. Tarapur power plant -> Maharasfra+ 380 MM 2. Rank-Printap Sagar power plant > Near Kots, Rayasthan -> 400 MW

2. Kalpakkan power plant -> Near Chennai, Tamilnager -> 490 MW 4. Namona power plant -> Otton prestore and any one building so Karnapar power plant -> Sunat district, Opyanot -> 470 MW a south a delight to a property of the particles Exert September Stands of Stands II Janor Just Band Ston whitelesser reactioned ten fact there The course of the opening franch such than water and where in the color of the Color of the color of the make a side of the many West file district his cold alamatan Santaalambana Santaalaan Page Nil-

DIESEL ELECTRIC POWER STATION

In an engine-generator set, the generator shaft is coupled to the Engine shaft. The engine converts chemical energy in fuel into mechanical energy. The generator converts mechanical energy into electrical energy.

Diesel engine is an excellent prime mover for electric generator capacities of from 100 hp to 5000 hp. The Diesel units used for electric generation are more reliable and long - lived piece of equipment compared with other types of plants.

Diesel engine power plants are installed where:

- Supply of coal and water is not available in desired quantity.
- Power is to be generated in small quantity for emergency services.
- Standby sets are required for continuity of supply such as in hospital, telephone exchange.

Advantages of diesel electric power plants:

The advantages of diesel power plants are listed below.

- Design and installations are very simple.
- Requires less water for cooling purpose.
- Standby losses are less as compared to other Power plants.
- Low fuel cost.
 Quickly started and put on load.
- Smaller storage is needed for the fuel.
- Layout of power plant is quite simple.
- No problem of Ash handling.
- Less supervision required.
- For small capacity, diesel power plant is more efficient as compared to steam power plant.
- Able to respond to varying loads without any difficulty.
- Occupy less space.
- Requires less operating and supervising staff as compared to steam power plant.
- Overall capital cost is lesser than that of steam power plant. Disadvantages of diesel electric power plants: The disadvantages of diesel power plants are listed below.

- High operating cost.
- High maintenance and lubrication cost.
- Fuel cost is more, since in India diesel is costly.
- The plant cost per kW is comparatively more.
- The life of diesel power plant is small due to high maintenance.
- Noise is a serious problem in diesel powerplant.
- Diesel power plant cannot be constructed for large scale.
- These can't be constructed in large size. Its capacity is limited.
- Diesel power plant is not economical.

Applications: •

They are quite suitable for mobile power generation and are widely used in Transportation systems consisting of railroads, ships, automobiles and airplanes.

- They can be used for electrical power generation incapacities from 100 to 5000 H.P.
- They can be used as standby power plants.
- They can be used as peak load plants for some other types of power plants.

Layout of diesel electric power plants:




Figure-1: Schematic layout of Diesel Power Plant




Figure-2: Schematic layout of Diesel Power Plant

Essential Component of Diesel Power Plant

- Engine
- Air intake system
- Exhaust system
- Fuel system
- Starting system
- Governing system
- Cooling system
- Lubrication system

Air Intake System:

- The air intake system conveys fresh air through pipes and ducts to
- Air intake manifold of 4s engine
- Scavenging pump inlet of 2s engine
- Supercharger inlet of supercharged engine





Figure: Air Intake System

The fresh air is first drawn and filtered to catch dirt from outsides air. The filters may be of dry or oil bath. Filtered air is then drawn by the engine during suction.

Exhaust System:

The exhaust system is used to discharge the engine exhaust to the atmosphere outside the plant.



The exhaust manifold takes exhaust gases from engine outlet and discharges the gases to the exhaust pipe. The muffler provided with the exhaust pipe reduces pressure in the exhaust line and reduce noise.

Fuel Supply system:

The fuel is delivered to the plant by railroad tank car, by truck or by barge and tanker and stored in the bulk storage situated outdoors for the sake of safety. From this main fuel tank, the fuel oil is transferred to the daily consumption tank by a transfer pump through a filter.




Figure: Fuel Storage & Supply System

The capacity of the daily consumption should be at least the 8-hour requirement of the plant. This tank is located either above the engine level so that the fuel flows by gravity to the injection pump or below the engine level and the fuel oil is delivered to the injection pump by a transfer pump driven from the engine shaft.

Fuel Injection system:

The five essential functions of a fuel injection system are:

- To deliver oil from the storage to the fuel injector.
- To raise the fuel pressure to the level required for atomization.
- To measure and control the amount of fuel admitted in each cycle.
- To control time of injection.
- To spray fuel into the cylinder in atomized form for thorough mixing and burning

Fuel injector is a mechanical device which is responsible for injecting the required amount of fuel into the engine to produce suitable air/fuel mixture for optimal combustion

The types of fuel injection methods are

- Common Rail
- Individual Pump Injection
- Distributor

Common Rail Fuel Injection:

In this type of injection, a pump supplies fuel under high pressure to a fuel header. This forces the fuel to each of the nozzle situated in the cylinders. A mechanically operated mechanism valve allows the fuel to enter in appropriate cylinder. The pressure relief and timing values are used to regulate the injection time and amount. The spring-loaded safety valve used as a check valve. When injection valve lifts to admit high pressure fuel to spray valve, its needle rises against the spring, when the pressure is vented to the atmosphere, the spring shut the valve.




Figure: Common Rail Fuel Injection System

Individual Pump Fuel Injection:

In this type of fuel injection system each fuel nozzle is connected to a separate injection pump. The pump controls the fuel charge and injection timing. Nozzles contain a delivery valve actuated by the fuel-oil pressure.




Figure: Individual Pump Fuel Injection System

Distributor System:

In this type of fuel injection system, the fuel is metered at a central point. The pump meters the fuel and time the injection. The pressurized fuel distributes to cylinders in correct firing order by cam operated poppet valves which open to admit fuel to the nozzles.




Figure: Distributor Fuel Injection System

Cooling System:

During the combustion process the peak gas temperature in the cylinder of an internal combustion engine is of the order of 2500 K. Metallic components are heated with very high temperature. Thus, cooling for the cylinder head, cylinder and piston is necessary.

Cooling of the engine reduce the possibility of fatigue cracking, knocking and preignition problem and increases the thermal efficiency.

Based on cooling medium two types of cooling system are generally used. These are

- Air as direct cooling system
- Liquid or indirect cooling system

Air cooling is used in small engine and portable engines. Liquid cooling is used in case of big engines. The cooling system can also be classified into two types:

- Open Cooling System: A Plant near the river may utilize the river water for cooling & discharging again the hot water into river. This type of cooling system is known as open cooling system.
- Closed Cooling System: The Cooling Water is circulated again & again and only water lost due to leakage, evaporation etc. is made up by taking make up water from supply source. Liquid cooling system is further classified as:
- Open cooling system
- Natural circulation (Thermo-system)
- Forced circulation system
- Evaporation cooling system

Open Cooling System:

This system is applicable only where plenty of water is available. The water from the storage tank is directly supplied through an inlet valve to the engine cooling water jacket. The hot water coming out of the engine is not cooled for reuse but it is discharged.

Natural circulation (Thermo-system)

The system is closed and designed so that the water may circulate naturally because of the difference in density of water at different temperatures. When the water is heated, its density decreases and it tends to rise, while the colder molecules tend to sink. Circulation of water then is obtained as the water heated to rise and the water-cooled in the radiator with the help of air passing over the radiator either by a fan.

Forced circulation system

Forced circulation cooling system that is closed one. The coolant (water or synthetic coolant) is circulated through the cylinder jacket with the help of a pump and driven by the engine.

Evaporation Cooling System:

In this method, water gets converted into steam after cooling the engine. This steam is cooled by the evaporative colling method.

Lubrication System:

Engine lubrication system provides lubricating oil to moving parts of the engine to reduce the friction between them. It reduces the wear & tear of the engine parts. This system consists of lubricating oil pump, oil tanks, filters, coolers, purifiers & connecting pipes. In this system the lubricating oil is stored in main lubricating oil tank. From this tank, oil is drawn by means of oil pump and then passed through the oil filter for removing impurities. Then this clean lubricating oil is delivered to the different points of the engine where lubrication is required. The oil cooler is provided in the system to keep the temperature of the lubricating oil as low as possible. It is then cooled through heat exchanger by means of cold water and then it is fed to the engine. The main function of the lubricant is:

- To reduce friction and wear between the parts having relative motion.
- To clean the surface by carrying away the carbon and metal particles caused by wear.
- To absorb shock between bearings and other parts and consequently reduce noise.
- To cool the surfaces by carrying away heat generated due to friction.
- To remove the heat generated due to friction and keeps the parts cool.

Engine lubrication system is classified as:

- Wet Sump lubrication system o Splash system o Semi pressure system
- Dry sump lubrication system
- Mist lubrication system

Starting System:

Initial rotation of the engine shaft is done by the starting system until the firing start and the engine runs with its own power. In case of small diesel generator set, the initial rotation of shaft is done by rotating the handle. But in case of large power plants, it is done by compressed air. This system includes storage compressed air tank, self-starter, auxiliary engines & electrical motors (battery) etc.

Site Selection for Plant

The following factors should be considered while selecting a site for diesel power plant.

- **Foundation subsoil conditions** Foundation of subsoil condition at a reasonable depth provides a strong support to the engine.
- Access to the site The site should be accessible for rail and road.
- **Distance from the load** Centre The location of the plant should be near to the load centre to reduce the cost of transmissions line, cost of maintenance and power load.
- Availability of water Sufficient water should be available at the site.
- Fuel transportation To minimize the transportation charge, the sites should be near to the source of fuel supply.

HYDEL POWER STATION

Hydroelectric power is the obtained from the energy of falling water whereas hydroelectric power plant is the power plant utilizing this potential energy of water at a high level for the generation of electrical energy. There is a conversion of hydraulic energy into mechanical energy followed by electrical energy.

Advantages of Hydroelectric power plants:

- Water is available throughout the year.
- Operational and maintenance cost is lower.
- The cost of fuel is nil.
- Hydro Plants are made for multiple purposes.
- The requirement of working staff is less.
- The cost of expenses is lower.
- It is a clean and non-polluting source of energy.
- No fuel is required.
- Dams are constructed near rivers. As the water level rises, the kinetic energy of water gets changed to potential energy.

Disadvantages of Hydroelectric power plants:


- Embankment construction cost is high.
- Land space requirement for set up is large.
- Water must be abundant to continue the process.
- Aquatic life is affected.
- Embankment areas need to be evacuated for flood plains.
- Highly expensive.
- Large areas of human habitation and agricultural fields are submerged.
- Dams can be made in limited areas.

General arrangement of storage type hydroelectric project

The major requirement for hydroelectric power plant is explained below.

- There must be availability of water in huge quantity at sufficient head. For this requirement construction of dam across a river or lake is required.
- The dam provides an artificial storage reservoir.

- A pressure tunnel is taken off from the reservoir to the valve house at the start of the penstock.
- The valve house contains main sluice valves for controlling water flow to the power station and automatic isolating valves for cutting off water supply in case the penstock bursts.
- A surge tank is provided just before the valve house for better regulation of water pressure in the system.
- Penstock to carry water.
- Water turbine
- Alternator



Layout of hydroelectric power plant

Working: From the reservoir the water is carried to valve house through pressure tunnel and from valve house to the water turbine through pipes of large diameter made of steel or reinforced concrete, called the penstock. The water turbine converts hydraulic energy into mechanical energy and the alternator coupled to the water turbine converts mechanical energy into electrical energy. Water after doing useful work is discharged to the tailrace.

Selection of site of hydel power plant.

The following factors should be considered while selecting site for hydroelectric power plants.

- Availability of Water: Huge quantity of water is required for hydro-electric power plants because it runs on the energy possessed by flowing water. Availability of water for plant depends on the amount of rainfall, losses of water and storage of water.
- Water Storage: Building of dam across the river is essential to store water for plant. Water falling from the top of the dam possesses high energy. Before constructing the dam near the river detail study on the geographical and topographical features of catchment area is required. Water Head: The available water head depends upon the topography of the area. Availability of

head of water has considerable effect on the cost and economy of power generation. In order to determine the most effective and economical head it is necessary to consider all possible factors which affect it.

- **Distance from Load Centre:** Hydroelectric power plant is usually located far away from the load centre.
- Accessibility of the Site: Adequate transportation facilities must be available.
- Water Pollution: Polluted water may cause excessive corrosion and damage to the metallic structures. Hence availability of good quality water is essential.
- Large Catchment Area: The reservoir must have a large catchment area so that level of water in the reservoir may not fall below the minimum required in dry season.
- Availability of Land: The land available should be cheap in cost and rocky in order to withstand the weight of the large building and heavy machinery.

List of hydro power stations with their capacities and number of units in the state

Sl.	Name of the Power Plant	Place	Capacity	No. of Units
No.				
1	Odisha Hydro Power	Rengali	250 MW	5 x 50 MW
2	Corporation Limited	Upper Kolab	320 MW	4 x 80 MW
3	(OHPCL)	Upper Indravati	600 MW	4 x 150 MW
4		Machkund	60 MW	3 x 23 MW
				3 x 17 MW
5		Burla	287.8 MW	2 x 49.5 MW
				2 x 32 MW
6		Chipilima	72 MW	
7		Balimela	510 MW	6 x 60 MW
				2 x 75 MW

Different types of Turbines & Generators used in hydro power plant:

- There are two main types of hydro-power turbines such as: Reaction turbine and Impulse turbine.
- The type of hydropower turbine selected for a project is based on the height of standing water, known as Head and the flow or volume of water over time.
- Other deciding factors include how deep the turbine must be set, turbine efficiency and cost. The different turbines used in hydro power plants are:
- Pelton turbine
- Francis's turbin Kaplan turbine